



Controllers and Environmental Sensors

Speed Controllers

CODE	VARIO SPEED CONTROLLER	BOX QTY
12943	CR5, 5 Speed Controller, On/Off. Reversible. Can be used to regulate more than one fan. Maximum load 100w Only suitable for Vario Range	6



12943: 5 Speed Controller

CODE	CA/LINEO ELECTRONIC SPEED CONTROLLERS	BOX QTY
12966	ELECTRONIC SPEED CONTROLLER 1.5A For models 100 Q V0 to 200 V0 inclusive	6
12967	ELECTRONIC SPEED CONTROLLER 2.5A For models 250 V0 and 315 V0	6
MSC3	ELECTRONIC SPEED CONTROLLER 3A	1



12966.

Environmental Sensors

CODE	SENSORS FOR VARIO & LINEO RANGE FANS	BOX QTY
12994	Humidity Sensor Measures ambient relative humidity (R.H.), and starts the fan when the R.H. exceeds 65%. The sensor can also be wired to allow the unit to be switched on when the R.H. is below 65%, and incorporates an over-run timer (adjustable between 3 and 20 minutes).	6
12998	PIR-Movement Detector, Detects the presence of a moving body within its sensor range, and starts the fan automatically. The built-in over-run timer can be adjusted between 3 and 20mins	6
12999	Timer Adjustable overrun timer (adjustable between 3 - 20 mins).	6
12992	Temperature Measures ambient room temperature, and starts the fan when the temperature exceeds the present value. Once the temperature drops below the present value (adjustable between 10° and 40°C), the unit will over-run for between 3 and 20 minutes (dependent on setting).	6

